



Samsung DCS Compact, DCS, iDCS 100, iDCS 500 Telephone Systems and Samsung SVMII voice mail:

1. From a display telephone, with the hand set down:
2. Press the transfer button and dial 200. The display will show:

{ENABLE CUS. PROG. PASSCODE}
3. Dial the code 1234. The display will show:

{ENABLE CUS. PROG-ENABLE}
4. Dial 1 to enable. Display will show: {ENABLE CUS. PROG-ENABLE}
5. Press the transfer button and the telephone returns to idle condition.
6. The telephone-programming door is open for 1 minute.
7. Press the transfer button and dial 505.
8. The display will show:

{OLD: 6010184:HHMM}

{NEW: WMMDDYY: 1445}
9. Enter the weekday, month, day, year, and the time in military format.

(0= Sunday, 1= Monday Etc.)
10. ALL TELEPHONES HAVE BEEN CHANGED.

40 State Route Thirty One #100
Flemington, NJ 08822
V. 908.782.8016 F. 908.788.8850

Providing Technology Solutions Since 1984